

BADLANDS Indian ILL-IND-S Illuminator RUN-BRAKE-TURN Module

Thank you for purchasing a Badlands Illuminator Module! We're sure that you will be completely satisfied with the performance and ease of installation of your new module. Before you get started, PLEASE read these instructions and helpful tips so that you understand how to install your module correctly. An improper installation will void the warranty.

FEATURES: All Badlands Illuminator Modules are designed to provide you running light, brake light and turn signal functions to each rear turn signal, all on (1) wire per side. **NOTE:** in order to use this module, the stock rear turn signals MUST be replaced with new RED LEDs. Our modules have a built-in Load Equalizer which will prevent a "rapid-flash" turn signal or indicating light. Now you understand the features of our Illuminator Module, let's talk about installation.

PLUG-N-PLAY: The wiring colors on our Illuminator Modules are defined in the color chart below. The ORANGE wire with installed fuse holder needs 12-volt switched or battery power. (**NOTE, we recommend that you connect the FUSED orange wire from our module directly to the (+) positive side of the battery while attaching the black wire to the (-) negative side of the battery.**)

INSTALLATION: The ILL-IND-S module offers Plug-n-Play technology, making installation quick and easy. Simply remove your seat to access the 6-position fender connection and battery. First disconnect the ground wire from the battery. Next unplug the **rear fender harness** connectors and plug our module in between. Connect our power wire (ORANGE) to battery (+) Positive, and ground wire (BLACK) to battery (-) and you're done.

Connecting your NEW Rear Fender Harness:

Yellow = Right Run/Brake/Turn (OUTPUT to Turn Signal)

Orange/White = License Plate Light

Gray = Left Run/Brake/Turn (OUTPUT to Turn Signal)

Black = Ground (for the Turn Signals, and Tail light)

Red/Yellow = Brake Light ONLY

Blue = Running Light ONLY

(NOTE when wiring the turn signals: You must wire our harness directly to the rear turn signals! NOT to the OEM tail light connector.)

ILL-IND-S: Plug-n-Play Indian Illuminator™ Run/Brake/Turn Module, With Rear Fender Harness (Fits all 2014-UP Scout, When replacing rear taillight and turn signals)

